IP D/N PoE PTZ Camera

ACM-8511

Ver. 120312

Hardware User's Manual

www.acti.com

0 PRECAUTIONS

1. **Read these instructions**
   All the safety and operating instructions should be read before the product is operated.
2. **Heed all warnings**
   All warnings on the product and in the instruction manual should be adhered to.



The symbol indicates the following items, please carefully read the description next to each symbol.

a. Failure to follow the safety instruction given may directly endanger people, cause damage to the system or to other equipment.
b. The requirements to make this device work, including hardware, computer settings, network settings, and operation procedures.
c. The tips to make using this device easier, more convenient and more efficient.

3. **Servicing**
   Do not attempt to service this video product yourself as opening or removing covers may expose you to dangerous voltage or other hazards. Refer all servicing to qualified service personnel.

Trademarks

All names used in this manual for hardware and software are probably registered trademarks of respective companies.

Liability

Every care has been taken during writing this manual. Please inform your local office if you find any inaccuracies or omissions. We cannot be held responsible for any typographical or technical errors and reserve the right to make changes to the product and manuals without prior notice.

FCC/CE Regulation

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses,

and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Table of Contents

1 INTRODUCTION

1.1 Package Contents

ACM-8511



Product CD



Terminal Blocks & Screw



Warranty Card



Accessory



1.2 Features and Benefits

This IP D/N PoE PTZ Camera is a cutting-edge digital video transmission device. It can compress and transmit real time images with outstanding images quality (D1, 720x480) at reasonable bandwidth through a standard TCP/IP network. That is because it is Ethernet ready and has the powerful ARM9 SoC with excellent system performance to offer dual streams of MPEG4/MJPEG, and both formats offer megapixel resolution. In addition, with these powerful hardware platform, excellent SDK support and powerful respective apparatuses (e.g. the transcoder), this IP D/N PoE PTZ Camera is your best choice building up either conventional IP surveillance system or intelligent IP surveillance system.

MPEG-4/MJPEG Dual Streaming

With excellent system performance, MPEG-4/MJPEG is supported. It brings superior image quality not only 30 frame per second in full D1 resolution.

Digital Time Code Embedded

The "Digital Time Code Embedded" function is to embed the recording time in the MPEG bit stream. Therefore, each image frame has its respective time when it was recorded. It is very useful when users want to find the video at an exact time or between a certain time intervals.

DDNS Supported

This IP D/N PoE PTZ Camera supports DDNS (Dynamic Domain Name Server); users can set this IP D/N PoE PTZ Camera at a virtual domain name (such as cam1.Taipei.xxx) at dynamic IP. Everyone can use the virtual domain name to view the video anywhere that has the access to the internet.

Build-in Hardware Motion Detection

No more external motion sensors are required. Each IP D/N PoE PTZ Camera can be set up to 3 detection areas. By tuning the object size and sensitivity, it is very reliable to fit into your environment. Besides, hardware motion detection delivers better sensitivity and responds faster than software motion detection.

Bundle Powerful Surveillance Software

To extend the capabilities of the IP outdoor rugged dome series, a

powerful surveillance program is included in the package and is very free to use. Users can easily utilize the existing PC to be a digital video recorder. Schedule recording and manual recording keep every important image recorded in the local hard disk. Reliable and accurate motion detection with instant warning makes you responsive in every condition. Quick and simple search and playback function lets you easily find the images you want.

Software Development Kit Support

This IP D/N PoE PTZ Camera can be integrated or controlled by user's application program through the Streaming Library or ActiveX control. With its high level programming interface, software developer's time and efforts to is highly reduced.

1.3 Safety Instructions

Don’t use the power supply with other voltages

This device is likely to be damaged or damage other equipments / personnel, if you use a power supply with different voltage than the one included with this device. All warranty of this product will be voided in the situations above.

Don’t open the housing of the product

Cleaning

Disconnect this video product from the power supply before cleaning.

Attachments

Do not use attachments not recommended by the video product manufacturer as they may cause hazards.

Water and Moisture

Do not use this video product near water, for example, near a bathtub, washbowl, kitchen sink, or laundry tub, in a wet basement, or near a swimming pool and the like.

Don’t use accessories not recommended by the manufacturer

- **Only install this device and the power supply in a dry place protected from weather**
- **Servicing**

Do not attempt to service this video product yourself as opening or removing covers may expose you to dangerous voltage or other hazards. Refer all servicing to qualified service personnel.

Damage Requiring service

Disconnect this video product from the power supply immediately and refer servicing to qualified service personnel under the following conditions.

1. When the power-supply cord or plug is damaged.
2. If liquid has been spilled, or objects have fallen into the video product.
3. If the video product has been exposed to rain or water directly.

4. If the video product does not operate normally by following the operating Instructions in this manual. Adjust only those controls that are covered by the instruction manual as an improper adjustment . Other controls may result in damage and will often require extensive work by a qualified technician to restore the video product to its normal operation.

Safety Check

Upon completion of any service or repairs to this video product, ask the service technician to perform safety checks to determine that the video product is in proper operating condition.

1.4 Physical Description



1. **<u>Power Input</u>**
   If your power input is DC12V.
   

2. **<u>Ethernet Port</u>**
   The IP D/N PoE PTZ Camera connects to the Ethernet via a standard RJ45 connector. Supporting NWAY, this IP D/N PoE PTZ Camera can auto detect the speed of local network segment (10Base-T/100Base-TX Ethernet).
3. **<u>Reset Button</u>**
   Step 1: Switch off IP D/N PoE PTZ Camera by disconnecting the power cable
   Step 2: Press and continue to hold the Reset Button. Reconnect the power cable while continuing to hold the reset button.
   Step 3: Keep holding the reset button depressed around 6 seconds, release the reset button. The unit will start up with factory default settings.
4. **<u>Audio Input</u>**
   The IP D/N PoE PTZ Camera supports audio input with earphone jack
5. **<u>Audio Output</u>**
   The IP D/N PoE PTZ Camera supports audio output with earphone jack
6. **<u>The I/O Terminal Connector</u>**

Used in applications for e.g. motion detection, event triggering, time lapse recording, alarm notifications, etc., the I/O terminal connector provides the interface to:

・1 transistor output - For connecting external devices such as relays and LED's. Connected devices can be activated by Output buttons on the Live View page or by an Event Type. The output will show as active (in Event Configuration > Port Status) if the alarm device is activated.

・1 digital input - An alarm input for connecting devices that can toggle between an open and closed circuit, for example: PIRs, door/window contacts, glass break detectors, etc. When a signal is received the state changes and the input becomes active (shown under Event Configuration > Port Status).


・Auxiliary power and GND

GND	Pin 1	Ground	Description
Auxiliary DC Power input (not to power this camera)	Pin 2	Electrically connected in parallel with the connector for the power supply, this pin provides an auxiliary connector for mains power to the unit. This pin can also be used to power auxiliary equipment, with a maximum current of 100mA.	Voltage: 12V DC, Max: 1.2W
Digital Input	Pin 3	Connect to GND to activate, or leave floating (or unconnected) to deactivate.	Must not be exposed to voltages greater than 30V DC.
Transistor Output	Pin 4	Uses an open-collector NPN transistor with the emitter connected to the GND pin. If used with an external relay, a diode must be connected in parallel with the load, for protection against voltage transients.	Max load = <100mA Max voltage = 24V DC (to the transistor)

Be sure to refer to the pin number above the connector before you connect to external DI/O devices.


Connect input/output devices to the camera as follows:

1. Attach the cables for the device securely to the supplied green connector block.
2. Once the cables are connected, push the connector block into the terminal


3.3V
DC TO DC
CONVERTER
FUSE 1A
+
-
POWER INPUT
EARTH GND
SW
GND
DC POWER
DI
DO
RELAY
DIODE
DEVICE
DI
DO
NPN
CAMERA

1.5 Basic Connections

Follow the procedures below to connect the IP D/N PoE PTZ Camera to the respective apparatuses.



1. Connect the power adaptor to IP D/N PoE PTZ Camera

2. Connect IP D/N PoE PTZ Camera's Ethernet port to an Ethernet (RJ45 connectors). If your IP D/N PoE PTZ Camera has PoE built-in, you can regard it as a PD and connect it directly to a PSE device like PoE switch.

3. Connect a PC to the Ethernet hub (RJ45 connectors)

NOTE: You may find a support package for help you getting familiar with PoE. Please visit our web site, and get the support document TS-00040.

1.6 Product Specification

			ACM-8511
Image	Device		1/4 inch CCD Image Sensor
	Size		1/4 inch
	Effective Pixels (HxV)		811x508(NTSC);795x596(PAL)
	Horizontal Resolution		480 TVL
Min. scene Illumination	Color		2.5 Lux at F1.8 (5600°K, 50IRE)
	B/W		0.07 Lux at F1.8 (5600°K, 50IRE)
Lens	Focal Length		4.2mm ~ 42mm
	Zoom Ratio		10x
	Aperture Ratio		F1.8(Wide),F2.9(Tele)
	Diagonal angle		56.4°(W)~6.1°(T)
	Digital Zoom		X1 ~ X10 variable
Synchronization	Sync. System		Internal
Day/Night Functions	Mechanical IR Cut Filter		N/A
Functions	Motion Detection		Yes (3 Windows)
	Electronic Shutter		1/60 ~ 1/120,000 sec. (NTSC) 1/50 ~ 1/120,000 sec. (PAL)
	Fixed Shutter		Yes (8 step)
	BLC		Super BLC,48 zone BLC
	AGC		AUTO (18dB max)
	White Balance		ATW /AWB / FIX
	Number of Preset		32 points
	Preset Tour		10 group
	Auto Scan		Yes
S/N Ratio	S/N Ratio		Better than 44 dB
PAN/TILT	Manual Speed	Pan	10° ~ 90° / sec.
		Tilt	10° ~70° / sec.
	Travel Range	Pan	354° (0° ~ 354°)
		Tilt	115° (-25° ~90°)
Video Compression	Compression		MPEG-4 SP, MJPEG selectable
	Picture Resolution		Full D1 (720 x 480 in NTSC, 720 x 576 in PAL) VGA (640 x 480 in NTSC, 640 x 480 in PAL) CIF (352 x 240 in NTSC, 352 x 288 in PAL) QCIF (160 x 112 in NTSC, 176 x 144 in PAL)
	Image Frame Rate		30 fps at full D1 resolution (NTSC) 25 fps at full D1 resolution (PAL)
Audio Input	Compression		8 kHz, Mono, PCM
	Audio Line Input		Unbalanced, 1.4Vp-p, 1Vrms, 3.5 mm Phone Jack
Audio Output	Compression		8 kHz, Mono, PCM
	Audio Line Output		Unbalanced, 1.4Vp-p, 1Vrms, 3.5 mm Phone Jack
Alarm	Digital Input		1, terminal block
	Transistor Ouput		1, terminal block
External I/O	Reset Button		Factory default
	LED		System status
Network	Ethernet		Ethernet(10/100Base-T), RJ-45 connector
	Protocol		TCP, UDP, IP, HTTP, DHCP, PPPoE, RTP, RTSP, FTP, SMTP, DNS, DDNS, NTP, ICMP, IGMP, ARP, 3GPP
Software	Web Browser		Microsoft Internet Explorer 6.0 or above
	SDK		ActiveX control, C SDK
	Security		Password protection: configured by the administrator
Operating	Temperature		0 ℃ ~ 45 ℃ (32 ℉ ~ 112 ℉)
Power	Power Requirement		PoE (IEEE802.3af) with Class 3
	Power Consumption		4.8 W (DV 12 V) ; 5.8 W (PoE)
Physical	Dimensions (WxHxD)		132 mm x 132 mm x 132 mm (5.20" x 5.20" x 5.20")
	Weight		570 g (1.26lb)